

# **DC/DC Converters**

TSN-1 Series, -1 A Switching Regulator

### **Features**

- Non-isolated converter for negative output
- Small size and low profile
- Pin compatible with LM79xx linear regulators
- No heatsink required
- High efficiency up to 96%
- Operation temp. range –40°C to +85°C
- Protection against overload, short circuit and over-temperature
- Fixed switching frequency
- Wide input range up to -32 VDC
- Excellent line / load regulation
- Low standby current
- 3-year product warranty



The new TSN-1 series step-down switching regulators are drop-in replacement for inefficient 79xx linear regulators. A high efficiency up to 96 % allows full load operation up to +70°C (+85°C with derating) ambient temperature without the need of any heat-sink or forced air cooling.

The TSN-1 switching regulators provide other significant features over linear regulators, i.e. better output accuracy ( $\pm 2$  %), lower standby current of ~2 mA and no requirement of external capacitors. They are suitable for negative output circuits. The high efficiency and low standby power consumption make these regulators an ideal solution for energy sensitive applications.

Models							
Order code		Input voltage	Output voltage	Output current	Efficiency typ.		
straight pins	angular pins	range / (nominal)		max.	@ Vin min.	@ Vin max.	
TSN 1-2450	TSN 1-2450A	-7.032 VDC (12 VDC)	-5.0 VDC		91.5 %	84.5 %	
TSN 1-2452	TSN 1-2452A	-7.032 VDC (12 VDC)	-5.2 VDC		92.0 %	85.0 %	
TSN 1-2460	TSN 1-2460A	-8.032 VDC (12 VDC)	-6.0 VDC		92.5 %	86.5 %	
TSN 1-2480	TSN 1-2480A	-10.532 VDC (12 VDC)	-8.0 VDC	-1.0 A	94.0 %	89.0 %	
TSN 1-2490	TSN 1-2490A	-11.5 – -32 VDC (24 VDC)	-9.0 VDC		94.5 %	90.5 %	
TSN 1-24120	TSN 1-24120A	-1532 VDC (24 VDC)	-12.0 VDC		96.0 %	92.0 %	
TSN 1-24150	TSN 1-24150A	-1832 VDC (24 VDC)	-15.0 VDC		96.0 %	93.5 %	

# TRACO<sup>®</sup> POWER

Input Specifications No load input current -3 mA typ. Reflected ripple current 100 mA typ. Input filter internal capacitors **Output Specifications** Voltage set accuracy ±2% (at full load) 1.0 % max. Regulation - Input variation - Load variation (10 - 100 %) 0.6 % max. Startup voltage overshoot 1.0 % max. Minimum load not required Ripple and noise (20 MHz Bandwidth) 5.0 - 5.2 VDC models: 50 mVpk-pk max. 6 - 15 VDC models: 75 mVpk-pk max Temperature coefficient ±0.015 % / °C max. Dynamic load response (change of 50% to 100% load) 5% of Vout mV peak variation 250 µS max. response time - start up time at nominal Vin, constant resistive load 15 mS typ. Startup time - rise time for 10 % to 90 % Vout 10 mS typ. Short circuit protection continuous, automatic recovery Capacitive load 5.0 - 5.2 VDC models: 1600 µF max. 1000 µF max. 6.0 - 9.0 VDC models: 12 – 15 VDC models: 470 µF max. **General Specifications** -40°C to +85°C Temperature ranges - Operating - Storage -55°C to +125°C 3.3 %/K above +70°C Derating MIL-STD-810F Thermal shock, mechanical shock & vibration Test conditions www.tracopower.com/products/mil810.pdf at +165°C (on internal IC) Overtemperature protection Humidity (non condensing) 95 % rel H max. Reliability, calculated MTBF (MIL-HDBK-217F, at +25°C, ground benign) >2′000′000 h Isolation voltage none Switching frequency 5.0 – 5.2 VDC models: 380 kHz typ. 6.0 - 15 VDC models: 500 kHz typ. **Physical Specifications** Casing material non-conductive plastic silicon (flammability to UL 94V-0 rated) Potting material Weight **3.1 g** (0.11 oz) Soldering profile max. +265°C / 10 sec. (wave soldering) Environmental compliance – Reach www.tracopower.com/products/reach-declaration.pdf RoHS directive 2011/65/EU – RoHS

All specifications valid at nominal input voltage, full load and +25°C after warm-up time unless otherwise stated.



# **Outline Dimensions**

## Straight pin version





#### Angular pin version (suffix A)



0.3 (0.01)

Pin-Out			
Pin	Single		
1	GND		
2	-Vin		
3	-Vout		

Dimensions in [mm], () = Inch Pin pitch tolerances:  $\pm 0.25 (\pm 0.01)$ Pin profile tolerance:  $\pm 0.1 (\pm 0.004)$ Other tolerances:  $\pm 0.5 (\pm 0.02)$ 

Specifications can be changed without notice! Make sure you are using the latest documentation, downloadable at www.tracopower.com